

Czujnik ruchu sensor LC

category: Kategorie > Elektryka - Electrics Parts



QR code:



1. Features

Our products adopt the most advanced imported internal sensor and circuit, when pedestrians into the sensing range light will start automatically. (light on), when they leave light will delay and shut down automatically.

- 1, Super saving electricity, power consumption 0.08 degrees per year;*
- 2, Wide working voltage, normally working in 100V-250V;*
- 3, Large power, impedance biggest load can reach 200W;*
- 4, Non-contact, simple installation (three-wire system);*

- 5, Delay time adjustable (006B specific);
- 6, Sensitivity adjustable (can be bright during the day 006B specific);
- 7, Adjustable sensing range (006B specific)
- 8, Strong anti-jamming capacity, more safe and reliable.

Components have been doing rigorous testing and screening, before delivery we have been doing aging test, please be assured to use

2. Specification

Working power: **AC100V~250V 50/60HZ**

Load power: **LED≤40W, Energy**

saving≤80W, Incandescent≤200W, Fan≤50W

Standby power: 0.0088W

Delay time: **15~300second**

Illumination: **5LUX~5000LUX**

Induction distance: **2~12M(default 5~8M)**

Sensor angle: **110~140degree**

3. Application

Corridor, toilet, basement, warehouse, garage, and other

places of automatic lighting, exhaust fan convulsions and other automatic control electrical, can be used for security purposes at the same time.

4. Attention

- 1.to turn off power when installation, must be installed by professional*
- 2.This switch can work normally after 45 seconds when electricity, it is infrared sensor preheat time*
- 3. Do not overload to use.*