

Miernik Cyfrowy 9208A

kategoria: Kategorie > Mierniki - Multimeter



Kod QR:



Function	Range	Accuracy
DC Voltage	200mV-1000V	$\pm(0.5\%+1\text{dgt})$
AC Voltage	20V-750V	$\pm(0.8\%+3\text{dgt})$
DC Current	20mA-20A	$\pm(0.8\%+1\text{dgt})$
AC Current	200mA-20A	$\pm(1.8\%+3\text{dgt})$
Resistance	200Ω-200MΩ	$\pm(0.8\%+1\text{dgt})$
Capacitance	2nF-20μF	$\pm(2.5\%+3\text{dgt})$
Frequency	2KHz-20KHz	$\pm(1.5\%+5\text{dgt})$
Temperature	-40°C~1000°C	$\pm(0.75\%+3\text{dgt})$
Diode Test	Yes	
Transistor Test	Yes	
Continuity Buzzer	Yes	

Auto Power Off	Yes	☐
Data Hold	No	☐
Logic Test	No	☐
Power Supply	9V Battery 6F22	☐
Maximum Display	1999	☐
Product Net Weight	300g	☐
Products Size	186×86×33mm	☐
Standard Accessories	Test Lead, Battery, Manual,Holster	